



MULTIPLES OF AMPERE SETTING (CONTINUOUS)

<p><b>GENERAL ELECTRIC</b></p> <p><b>Sensor Rating (Amperes)</b>          200, 400, 600, 800, 1000, 1200          1600, 2000, 2500, 3000 amperes</p> <p><b>Voltage Rating</b>          600 volts ac</p> <p><b>Frequency Rating</b>          50/60 Hertz</p>	<p>INSULATED-CASE CIRCUIT BREAKER</p> <p><b>POWER BREAK<sup>®</sup></b></p> <p><b>With SelectTrip<sup>™</sup></b></p> <p>Types TPR, THR, TPRR, THRR</p> <p>Long-time, Short-time          and Instantaneous Time-current Curves</p> <p><small>(Curves apply at 50/60 Hertz and from -20 C to +55 C ambient)</small></p>	<p><b>GES-6149A</b></p> <p><b>Adjustments</b></p> <p>Long-time-delay Unit: Continuous current settings are 50, 60, 70, 80, 90 and 100% of sensor ratings.</p> <p>Magnetic-delay Unit: Pick-up current settings are 4x, 5x, 6x, 7x, and 8x multiples of long-time unit setting thru 2500 amperes, and 2x, 3x, 4x, 5x and 7x for 3000 amperes.</p> <p>Instantaneous Over-ride: Set at 15x sensor ampere rating. For sensor ratings thru 2500 amperes, and 12x for 3000 amperes.</p>
---	---	---